

CPU BOARD		MASTER DISPLAY BOARD		
Connection		Connection	Function	Colour
1J3-4		4J7- 3	BLANKING	BLU/WHT
1J5-1		4J7- 4	BCD - D1	BLU/YEL
1J5-2		4J7- 2	BCD - C1	BLU/ORN
1J5-3		4J7- 1	BCD - B1	BLU/RED
1J5-4		4J7- 5	BCD - A1	BLU/BRN
1J5-5		4J7- 8	BCD - D2	BLU/GRY
1J5-6	*KEY	N/C	NONE	
1J5-7		4J7- 7	BCD - C2	BLU/VIO
1J5-8		4J7- 6	BCD - B2	BLU/BLK
1J5-9		4J7- 9	BCD - A2	BLU/GRN
1J6-1		4J5- 4	STROBE 9	VIO/GRY
1J6-2		4J5- 5	STROBE 1	VIO/BLK
1J6-3		4J5-14	STROBE 16	VIO/BLU
1J6-4		4J5-16	STROBE 15	VIO/GRN
1J6-5		4J5-17	STROBE 14	VIO/YEL
1J6-6		4J5-13	STROBE 13	VIO/ORN
1J6-7	*KEY	N/C	NONE	
1J6-8		4J5-12	STROBE 12	VIO/RED
1J6-9		4J5-15	STROBE 11	VIO/BRN
1J7-1		4J5- 2	STROBE 10	BRN/GRY
1J7-2		4J5- 3	STROBE 8	BRN/VIO
1J7-3		4J5-11	STROBE 7	BRN/BLU
1J7-4		4J5-10	STROBE 6	BRN/GRN
1J7-5		4J5- 9	STROBE 5	BRN/YEL
1J7-6		4J5- 8	STROBE 4	BRN/ORN
1J7-7		4J5- 7	STROBE 3	BRN/RED
1J7-8	*KEY	N/C	NONE	
1J7-9		4J5- 6	STROBE 2	BRN/BLK
1J8-1		4J5- 1	COMMAS 3&4	BRN/WHT
1J8-2		4J5-18	COMMAS 1&2	VIOLET

KEY: Black=BLK, Brown=BRN, Red=RED, Orange=ORN, Yellow=YEL,
Green=GRN, Blue=BLU, Violet=VIO, Grey=GRY, White=WHT

Display Wiring Harness
Williams System 7 starting from #500:



ISSUE NUMBER 1.1 (25 OCT 2008)
CREATED BY: Richard Harvey
www.firepowerpinball.com